

Applications

- The TIMER can be programmed with 10 different functions.
- Module can be used for customising siren output times, beam bypass, guard awake and auto gate & garage door closure applications.
- A variety of applications and functions are visualised for this product and with a bit of imagination the unit will solve various security installation issues.

Features

- Timed Relay output from 1 second to 59 minutes & 59 seconds
- Timed Relay output from 1 Minute to 23 hours
- Auto garage door closure
- Guard awake timer
- Pulse stretcher
- Counter
- Count down trigger output
- False alarm prevention
- Momentary to Latching



Specifications

- Power input range: 10V ~ 14V DC
- Functions: 1 second to 59 minute timer output
- 1 minute to 24 hours timer output
- Auto door closure
- Guard awake timer
- Pulse stretcher
- Counter
- Count down trigger output
- False alarm prevention
- Momentary to latching
- 1 second to 59 minute timer re-triggable
- Trigger Input: Positive / Negative
- Reset Input: Normally Open potentially free
- Relay output Load @ 12V DC: 1AMP
- Dimensions: 52 X 65mm (PCB)

Description

Multifunction Timer Module

Order Code

TIMER